



# EB125P

## 1,200W & 575W Ballast

This ballast can operate on any worldwide mains supply and has built-in DMX for remote control of stop/start & dimming. It features Power Factor Correction to minimise current draw and maximise ignition performance. It is built using a unique modular system which allows the main Power Electronics to be simply unplugged and even interchanged with modules from our 4,000W or 1,800W ballasts.



### Specification

Max. Lamp Power	1.2kW	Power Cable	Integral
Power Options	1.2kW, 575W	Over Temp Protection	✓
Low Noise Option	✓	Luminaire Socket Options	✓
300Hz Output Option	✓	DMX Control	✓
Input Voltage Range	90-265V AC	Input Circuit Breaker	✓
Input Apparent Power	1.4/0.6kVA	Interchangeable Modules	✓
Input Real Power	1.4/0.6kW	Max. Ambient Temp	50°C/122°F
Current Draw (230V/120V)	6.1A/11.7A	Width	225mm/8.9"
Power Factor	0.98	Height	115/4.5"
Dimming to 50%	✓	Depth	350mm/13.8"
Lamp Running Indication	✓	Weight	7.5kg/16.6lb

**POWER GEMS LTD**  
 15 Wharfside Business Park, Irlam Wharf Road,  
 Irlam, Manchester M44 5PN. United Kingdom  
 Tel +44 (0) 161 776 7030

**POWER GEMS CORPORATION**  
 7034 Sophia Avenue, Van Nuys,  
 California 91406. USA  
 Tel +1 818 376 1800