



EB1812P

18,000W & 12,000W Ballast

A rugged, proven product in use in many locations around the globe. The ballast is Power Factor Corrected (ALF) which minimises current draw and maximises ignition performance. It can be supplied with one or two output sockets and is compatible with the heads from all major manufacturers.



Specification

Max. Lamp Power	18kW	Power Cable	Optional
Power Options	18kW, 12kW	Over Temp Protection	✓
Low Noise Option	✓	Line Over-voltage Trip	>265V
300Hz Output	Optional	Line Under-Voltage Trip	<190V
Input Voltage Range	195-260V AC	Luminaire Socket Options	✓
Input Circuit Breaker	✓	Diagnostic System	✓
Input Apparent Power	19.4kVA/13.1kVA	Max. Ambient Temp	45°C/113°F
Input Real Power	19kW/12.8kW	Width	330mm/13"
Current Draw (@230V)	85.2A (@18kW)	Height	555mm/21.8"
Power Factor	0.98	Depth	470mm/18.5"
Dimming to 50%	✓	Weight (excl cart)	55kg/121lb
Lamp Running Light	✓	Accessories	DMX, Cart.

POWER GEMS LTD
 15 Wharfside Business Park, Irlam Wharf Road,
 Irlam, Manchester M44 5PN. United Kingdom
 Tel +44 (0) 161 776 7030

POWER GEMS CORPORATION
 7034 Sophia Avenue, Van Nuys,
 California 91406. USA
 Tel +1 818 376 1800